



PRODUCT-DETAILS

PSTX37-600-70

PSTX37-600-70 Softstarter - 37 A - 208 ... 600
V AC



genel Bilgi

Küresel Ticari Takma Ad	PSTX37-600-70
Geniştirilmiş Ürün Türü	PSTX37-600-70
Ürün Kimliği	1SFA898104R7000
ABB Tür Tanımı	PSTX37-600-70
EAN	7320500501320
Katalog Açıklaması	PSTX37-600-70 Softstarter - 37 A - 208 ... 600 V AC

Uzun Açıklama

The softstarter PSTX37-600-70 has a rated maximum operational current of 37 A with an operating voltage span from 208...600 V AC. The rated control voltage is between 100...250 V AC at 50/60 Hz. PSTX features a three-phase control soft start and stop through a voltage or a torque ramp. It has built-in bypass for easy installation and energy saving. A RUN, TOR and Event signal is available from relay outputs in NO (normally open state). The PSTX has functions such as current limit, kickstart, analog output, EOL, motor heating and pump cleaning. PSTX also features features jog, braking, stand-still brake, diagnostics, sequence start and emergency/fire pump mode as standard. To interact with PSTX, it has a detachable full graphic display with IP66 and 4x outdoor rating. There are four ways to communicate with PSTX. It can be done by hardwire inputs Start/Stop/Reset of fault, and by three programmable digital inputs. Another popular option is the built-in Fieldbus communication Modbus RTU and incl optional ANYBUS modules with every major protocol such as for example Profinet, Profibus, Modbus TCP, Ethernet IP and others. Another way to communicate with PSTX is to use an external adaptor and a Fieldbus plug. PSTX is the complete alternative for any motor starting application. It's suitable for medium to large-sized three-phase motors with nominal currents from 30...1250 A inline connection or 52...2160 A inside delta connection. Typical applications are, for example, pumps, fans, compressors, and conveyors.

Ordering

Minimum Sipariş Miktarı	1 piece
Gümrük Tarifesi numarası	85371091

Popular Downloads

Veri Sayfası, Teknik Bilgi	1SFC132012C0201
Talimatlar ve Kılavuzlar	1SFC132428M0201
Talimatlar ve Kılavuzlar (Bölüm 2)	1SFC132081M0201
Instructions and Manuals (Part 3)	1SFC132060M0201
CAD Dimensional Drawing	2CDC001079B0201
Wiring Diagram	N/A

Dimensions

Ürün Net Genişliği	150 mm
Ürün Net Yüksekliği	314 mm
Ürün Net Derinlik / Uzunluk	198 mm
Ürün Net Ağırlığı	4.6 kg

Technical

Nominal Çalışma Gerilimi	208 ... 600 V AC
Rated Control Supply Voltage (U _s)	100 ... 250 V AC

Rated Control Circuit Voltage (U _c)	24 V DC
Nominal Frekans (f)	50/60 Hz Main Circuit 50 / 60 Hz
Rated Operational Power - In-Line Connection (P _e)	(230 V) 9 kW (400 V) 18.5 kW (500 V) 22 kW
Nominal Çalışma Akımı - Hat İçi Bağlantı (I _e)	37 A
Rated Operational Power - Inside Delta Connection	at 230 V 15 kW at 400 V 30 kW at 500 V 37 kW
Rated Operational Current - Inside Delta Connection	64 A
Hizmet Faktörü Yüzdesi	100 %
Overload Protection	Built-in electronic overload protection
Integrated Electronic Overload	Yes
Starting Capacity at Maximum Rated Current I _e	4xle for 10s
Ramp Time	1 ... 120 second [unit of time]
Initial Voltage During Start	10 ... 99 %
Step Down Voltage Special Ramp	100 ... 10 %
Current Limit Function	1.5 ... 7.5 xle
Switch for Inside Delta Connection	Yes
Run Signal Relay	Yes
By-pass Signal Relay	Yes
Fault Signal Relay	Yes
Overload Signal Relay	Yes
Analog Çıkışlar	0...10 V, 0...20 mA, 4...20 mA
Signal Indication Ready to Start/Standby ON (LED)	Green
Sinyal göstergesi çalışıyor R (LED)	Green
Signal Indication Protection (LED)	Yellow
Signal Indication Fault (LED)	Red
İletişim	Modbus-RTU; Modbus-TCP; Ethernet-IP; EtherCAT; DeviceNet; CANopen; Profibus; Profinet; BACnet-IP; BACnet-MSTP
Koruma Derecesi	acc. to IEC 60529, IEC 60947-1, EN 60529 Main Terminals IP00
Terminal Türü	Cable Clamp
Connecting Capacity Main Circuit	Hole Diameter 8.5 mm
Connecting Capacity Control Circuit	Rigid 1 x 2.5 mm ²
Connecting Capacity Supply Circuit	Rigid 1 x 2.5 mm ²
Sıkma Torku	Main Circuit 8 N·m
Ürün Ana Türü	PSTX37
Function	Auto phase sequence detection Automatic restart Current limit Current limit ramp Dual current limit

	Dynamic brake
	Electricity metering
	Electronic overload Time-to-cool
	Emergency mode
	Event log
	Full voltage start
	Jog with slow speed, forward and reverse
	Keypad password
	Kick start
	Limp mode with two-phase motor control if one set of thyristors is shorted
	Motor heating
	Pre-start function
	Pump cleaning
	Real time clock
	Sequence start
	Soft start with torque control
	Soft start with voltage ramp
	Soft stop with torque control
	Soft stop with voltage ramp
	Stand still brake
	Start reverse (external contactors)
	Thyristor runtime measurement
	Torque limit
	Voltage sags detection
Protection Function	Bypass open protection; Current imbalance protection; Current underload protection; Dual overload (separate overload for start and run); Earth fault protection / ground fault protection; Electronic overload protection, EOL; Extension IO failure protection; Fieldbus failure protection; HMI failure protection; Locked rotor protection; Max number of starts/hour; Over voltage protection; Phase reversal protection; Power factor underload protection; PT-100 connection; PTC connection; Too long current limit protection; Too long start time protection; Under voltage protection; User defined protection; Voltage imbalance protection
Warning Details	Current imbalance warning; Current underload warning; Electronic overload Time-to-trip; EOL warning; Faulty fan warning; Locked rotor warning; Motor runtime limit warning; Over voltage warning; Phase loss warning (for standby); Power factor underload warning; Short circuit warning (for Limp mode); THD(U) - Total Harmonic Distortion warning; Thyristor overload warning (SCR); Under voltage warning; Voltage imbalance warning

Technical UL/CSA

Beygir Gücü Anma UL/CSA	(200 ... 208 V AC) Three Phase 10 Hp (220 ... 240 V AC) Three Phase 10 Hp (440 ... 480 V AC) Three Phase 25 Hp (550 ... 600 V AC) Three Phase 30 Hp
Maximum Operating Voltage UL/CSA	Main Circuit 600 V
Tightening Torque UL/CSA	Main Circuit 70.8

Environmental

Ortam Hava Sıcaklığı	Operation -25 ... +60 °C Storage -40 ... +70 °C
----------------------	--

Material Compliance

Conflict Minerals Reporting Template (CMRT)	9AKK108467A5658
REACH Declaration	2CMT2022-006481

RoHS Bilgileri	2CMT2022-006500
RoHS Durumu	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
SCIP	46ee42b5-0784-4f84-a200-fba43f921301 China (CN)
Toxic Substances Control Act - TSCA	2CMT2023-006524
AEEE B2C / B2B	Business To Business
AEEE Kategorisi	5. Small Equipment (No External Dimension More Than 50 cm)

Certificates and Declarations

CQC Certificate	CN: CQC2014010304744405 / SE: CQC2014010304724380
Declaration of Conformity - CCC	CN: 2020980304001091 / SE: 2020980304001489
Uygunluk Beyanı - CE	2CMT005209
DNV Sertifikası	TAE000087N

Container Information

Paket Düzey 1 Genişlik	200 mm
Paket Seviye 1 Derinlik / Uzunluk	282 mm
Paket Seviye 1 Yükseklik	388 mm
Paket Seviye 1 Brüt Ağırlık	5.6 kg
Paket Düzey 1 EAN	7320500501320
Paket Seviye 1 Birimler	box 1 piece

External Classifications and Standards

Nesne Sınıflandırma Kodu	Q
ETIM 7	EC000640 - Soft starter
ETIM 8	EC000640 - Soft starter
ETIM 9	EC000640 - Soft starter
eSınıf	V11.0 : 27370907
UNSPSC	39121521
IDEA Granüler Kategori Kodu (IGCC)	4740 >> Soft starter

Accessories

Identifier	Description	Type	Quantity	Unit Of Measure
1SFN074307R1000	LW110 Terminal Enlargement	LW110	1	piece
1SFA899314R1001	PSCA-1 USB cable	PSCA-1	1	piece
1SFA899300R1001	AB-PROFIBUS-1 Communication Module	AB-PROFIBUS-1	1	piece
1SFA899300R1002	AB-DEVICENET-1 Communication Module	AB-DEVICENET-1	1	piece
1SFA899300R1003	AB-MODBUS-RTU-1 Communication Module	AB-MODBUS-RTU-1	1	piece
1SFA899300R1006	AB-ETHERNET-IP-2 Communication Module	AB-ETHERNET-IP-2	1	piece
1SFA899300R1008	AB-MODBUS-TCP-2 Communication Module	AB-MODBUS-TCP-2	1	piece
1SFA899300R1010	AB-PROFINET-IO-2 Communication Module	AB-PROFINET-IO-2	1	piece
1SFA899300R1011	AB-BACNET-MSTP-1 Communication Module	AB-BACNET-MSTP-1	1	piece
1SFA899300R1012	AB-ETHERCAT-IP-2 Communication Module	AB-ETHERCAT-IP-2	1	piece
1SAJ622000R0101	DX122-FBP.0 IO-Module for UMC100 DI 110/230VAC, supply 24VDC	DX122-FBP.0	1	piece
1SFA896312R1002	PS-FBPA Fieldbus plug kit	PS-FBPA	1	piece

katagori

Drives → Softstarters → Softstarters → PSTX Softstarters → PSTX37

Low Voltage Products and Systems → Control Products → Softstarters → Softstarters → PSTX Softstarters → PSTX37

